





TBL25

A 4W, 25V transformer with 5 taps at -3dB levels each, and 7" color-coded leads.



TBL70

A 4W, 70V transformer with 5 taps at -3dB levels each, and 7" color-coded leads.



APPLICATION	Intended Use: Program Material: Installation:	Indoor environment Signal tones, voice and music • Desired tap/common primary leads connected to the output of a constant voltage amplifier • Secondary/common attached to a nominal 8 Ohm loudspeaker	Indoor environment Signal tones, voice and music • Desired tap/common primary leads connected to the output of a constant voltage amplifier • Secondary/common attached to a nominal 8 Ohm loudspeaker
AUDIO PERFORMANCE	Primary Voltage: Maximum Power Rating: Primary Taps (-3 dB Steps): Secondary Load: Frequency Response: Insertion Loss:	25V 4W 0.25W, 0.50W, 1W, 2W, 4W 8 Ohms, Nominal 100Hz - 15kHz 1.0 dB	70V 4W 0.25W, 0.50W, 1W, 2W, 4W 8 Ohms, Nominal 100Hz - 15kHz 1.0 dB
MECHANICAL SPECIFICATIONS	Dimensions: Primary Connection: Secondary Connection:	1 7/16" (H) x 1 1/16" (W) x 1 1/2" (D) 7", Color-coded, Pre-tinned Leads 6", Color-coded, Pre-tinned Leads	1 7/16" (H) x 1 1/16" (W) x 1 1/2" (D) 7", Color-coded, Pre-tinned Leads 6", Color-coded, Pre-tinned Leads
RECOMMENDED QUAM COMPONENTS	Loudspeaker:	Quam 8 Ohm loudspeakers	Quam 8 Ohm loudspeakers

