

.....®
CALRAD
ELECTRONICS

819 N. Highland Ave.
Los Angeles, CA 90038
Tel: (323) 465-2131, Fax: (323) 465-3504
Visit us on the web at www.CALRAD.com

40-DCT-1-E DIGITAL TO STEREO AUDIO CONVERTER



The 40-DCT-1-E converts a digital audio signal source from a digital coax RCA jack or optical toslink jack and converts to an analog stereo audio signal L+R RCA output jacks. Compact size and easy to install.

SPECIFICATIONS:

- Converts Digital Audio to Analog Audio
- Digital Input: Coaxial and Optical
- Digital Audio Format: LPCM
- Stereo Audio Output: Analog (L+R Audio)
- Sampling Frequency Response: 32, 44.1, 48 and 96 KHz Sample Rate
- 24-bit S/PDIF incoming bit stream on left and right channels
- DC Input Connector: 5.5mm x 2.1mm x 9.5mm
- Power Supply: 5V DC @ 1A
- Weight: 78g
- Dimensions: 51mm (L) x 41mm (W) x 26mm (H)

Important Note:

- This Device will not decode 5.1. It will only convert 2-Channel digital stereo (LPCM) input signals to analog stereo output. This will not work with TV's that only output 5.1 channel digital signals.

Example Diagram:

