

NF44E-13

Relay

1SBH137001R1344

NF44E-13 100-250V50/60HZ-DC Contactor

NF contactor relays are used for switching

auxiliary and control circuits. NF contactor relays include an electronic coil interface accepting a wide control voltage Uc min. ... Uc max. Only four coils cover control voltages between 24...500 V 50/60 Hz or 20...500 V DC. NF contactor relays can

manage large control voltage variations. One coil can be used for different control voltages used worldwide without any coil change. NF contactor relays have built-in

surge protection and do not require additional surge suppressors. - Poles: 8pole contactor relays with a non-removable front-mounted auxiliary contact block (mechanically-linked auxiliary contacts compliant with Annex L of IEC 60947-5-1 and including the "Mechanically Linked" symbol on the contactor relay side) -Control Circuit: AC or DC operated -Accessories: a wide range of Accessories

3471523100732



Product Guide » ABB1SBH137001R1344

# NF44E-13

**General Information** 

Catalog Description:

Long Description:

Product ID:

EAN:

Extended Product Type:

Print View.. Print to Pdf..

### Search ⇒ OK Products & Services only



Q

rour preference	
Egypt	$\checkmark$ $\rightarrow$ O
English	▼ → O
ABB contact for	Egypt

-

⇒ OK

Select another country

Categories

Products » Low Voltage Products and Systems » Control Products » Contactors » Block Contactors

is available.

#### Ordering

EAN:	3471523100732
Minimum Order Quantity:	1 piece
Customs Tariff Number:	85369085

## Dimensions

Product Net Width:	45 mm
Product Net Depth:	110.5 mm
Product Net Height:	86 mm
Product Net Weight:	0.320 kg

## **Container Information**

Package Level 1 Units:	1 piece
Package Level 1 Width:	87 mm
Package Level 1 Length:	113 mm
Package Level 1 Height:	47 mm
Package Level 1 Gross Weight:	0.32 kg
Package Level 1 EAN:	3471523100732
Package Level 2 Units:	36 piece
Package Level 3 Units:	864 piece

#### Technical

Technical	
Number of Auxiliary Contacts NO:	4
Number of Auxiliary Contacts NC:	4
Standards:	IEC 60947-5-1 and EN 60947-5-1, UL 508, CSA C22.2 N°14
Rated Operational Voltage:	Auxiliary Circuit 690 V Main Circuit 690 V
Rated Frequency (f):	Auxiliary Circuit 50 / 60 Hz
Conventional Free-air Thermal Current (I <sub>th</sub> ):	acc. to IEC 60947-5-1, q = 40 °C 16 A
Rated Operational Current AC-15 (I <sub>e</sub> ):	(220 / 240 V) 4 A (24 / 127 V) 6 A (400 / 440 V) 3 A (500 V) 2 A (690 V) 2 A
Rated Short-time Withstand Current (I <sub>cw</sub> ):	for 0.1 s 140 A for 1 s 100 A
Maximum Electrical Switching Frequency:	AC-15 1200 cycles per hour DC-13 900 cycles per hour
Rated Operational Current DC-13 (I <sub>e</sub> ):	(110 V) 0.55 A / 60 W (125 V) 0.55 A / 69 W (220 V) 0.27 A / 60 W (24 V) 6 A / 144 W (250 V) 0.27 A / 68 W (400 V) 0.15 A / 60 W (48 V) 2.8 A / 134 W (500 V) 0.13 A / 65 W (600 V) 0.1 A / 60 W (72 V) 1 A / 72 W
Rated Insulation Voltage (Ui):	acc. to UL/CSA 600 V acc. to IEC 60947-5-1 and VDE 0110 (Gr. C) 690 V
Rated Impulse Withstand Voltage (U <sub>imp</sub> ):	6 kV
Maximum Mechanical Switching Frequency:	6000 cycles per hour
Rated Control Circuit Voltage (U <sub>c</sub> ):	50 Hz 100250 V 60 Hz 100250 V DC Operation 100250 V
Operate Time:	Between Coil De-energization and NC Contact Closing 1398 ms Between Coil De-energization and NO Contact Opening 1195 ms Between Coil Energization and NC Contact Opening 3890 ms Between Coil Energization and NO Contact Closing 4095 ms
Connecting Capacity-Auxiliary Circuit:	Flexible with Ferrule 1/2x 0.75 2.5 mm <sup>2</sup> Flexible with Insulated Ferrule 1x 0.75 2.5 mm <sup>2</sup> Flexible with Insulated Ferrule 2x 0.75 1.5 mm <sup>2</sup> Rigid 1/2x 12.5 mm <sup>2</sup>

CONNECTING CANACITY-CONTROL CITCUIT	
	Flexible with Ferrule 1/2x 0.75 2.5 mm <sup>2</sup> Flexible with Insulated Ferrule 1x 0.752.5 mm <sup>2</sup> Flexible with Insulated Ferrule 2x 0.751.5 mm <sup>2</sup> Rigid 1/2x 12.5 mm <sup>2</sup>
Wire Stripping Length:	Auxiliary Circuit 10 mm Control Circuit 10 mm
Degree of Protection:	acc. to IEC 60529, IEC 60947-1, EN 60529 Auxiliary Terminals IP20 acc. to IEC 60529, IEC 60947-1, EN 60529 Coil Terminals IP20
Terminal Type:	Screw Terminals
Environmental	
Ambient Air Temperature:	Close to Contactor for Storage -60+80 °C Near Contactor for Operation in Free Air -40 +70 °C
Maximum Operating Altitude Permissible:	3000 m
Resistance to Shock acc. to IEC 60068-2-27:	Closed, Shock Direction: B1 25 g Open, Shock Direction: B1 5 g Shock Direction: A 30 g Shock Direction: B2 15 g Shock Direction: C1 25 g Shock Direction: C2 25 g
Resistance to Vibrations acc. to IEC 60068-2-6:	5300 Hz 4 g closed position / 2 g open position
RoHS Status:	Planned to follow EU Directive 2002/95/EC August 18, 2005 and amendment
	after 2008 Q1
Technical UL/CSA Tightening Torque UL/CSA:	
Technical UL/CSA	after 2008 Q1 Auxiliary Circuit 11 in·lb Control Circuit 11 in·lb
Technical UL/CSA Tightening Torque UL/CSA: Certificates and Declarations (Do	after 2008 Q1 Auxiliary Circuit 11 in·lb Control Circuit 11 in·lb
Technical UL/CSA Tightening Torque UL/CSA: Certificates and Declarations (Do CB Certificate:	after 2008 Q1 Auxiliary Circuit 11 in·lb Control Circuit 11 in·lb Document Number)
Technical UL/CSA Tightening Torque UL/CSA: Certificates and Declarations (Do CB Certificate: CCC Certificate:	after 2008 Q1 Auxiliary Circuit 11 in·lb Control Circuit 11 in·lb Document Number) CB_SE_70920A1M2
Technical UL/CSA Tightening Torque UL/CSA:	after 2008 Q1 Auxiliary Circuit 11 in·lb Control Circuit 11 in·lb Comment Number) CB_SE_70920A1M2 CCC_2011010303465426
Technical UL/CSA Tightening Torque UL/CSA: Certificates and Declarations (Do CB Certificate: CCC Certificate: cUL Certificate: Declaration of Conformity - CE:	after 2008 Q1   Auxiliary Circuit 11 in·lb   Control Circuit 11 in·lb   Document Number)   CB_SE_70920A1M2   CCC_2011010303465426   UL_20091127-E252354-2-1
Technical UL/CSA Tightening Torque UL/CSA: Certificates and Declarations (Do CB Certificate: CCC Certificate: cUL Certificate:	after 2008 Q1   Auxiliary Circuit 11 in·lb   Control Circuit 11 in·lb   Document Number)   CB_SE_70920A1M2   CCC_2011010303465426   UL_20091127-E252354-2-1   1SBD250166C2000
Technical UL/CSA Tightening Torque UL/CSA: Certificates and Declarations (Do CB Certificate: CCC Certificate: cUL Certificate: Declaration of Conformity - CE: DNV Certificate: EAC Certificate:	after 2008 Q1   Auxiliary Circuit 11 in·lb   Control Circuit 11 in·lb   Document Number)   CB_SE_70920A1M2   CCC_2011010303465426   UL_20091127-E252354-2-1   1SBD250166C2000   DNV_E11683
Technical UL/CSA Tightening Torque UL/CSA: Certificates and Declarations (Do CB Certificate: CCC Certificate: cUL Certificate: Declaration of Conformity - CE: DNV Certificate: EAC Certificate: GL Certificate:	after 2008 Q1   Auxiliary Circuit 11 in·lb   Control Circuit 11 in·lb   Document Number)   CB_SE_70920A1M2   CCC_2011010303465426   UL_20091127-E252354-2-1   1SBD250166C2000   DNV_E11683   EAC_RU C-FR ME77 B01006
Technical UL/CSA Tightening Torque UL/CSA: Certificates and Declarations (Do CB Certificate: CCC Certificate: cUL Certificate: Declaration of Conformity - CE: DNV Certificate: EAC Certificate: GL Certificate: GOST Certificate:	after 2008 Q1   Auxiliary Circuit 11 in·lb   Control Circuit 11 in·lb   Document Number)   CB_SE_70920A1M2   CCC_2011010303465426   UL_20091127-E252354-2-1   1SBD250166C2000   DNV_E11683   EAC_RU C-FR ME77 B01006   GL_3786612HH
Technical UL/CSA Tightening Torque UL/CSA: Certificates and Declarations (Do CB Certificate: CCC Certificate: cUL Certificate: Declaration of Conformity - CE: DNV Certificate: EAC Certificate: GL Certificate: GST Certificate: LR Certificate:	after 2008 Q1   Auxiliary Circuit 11 in·lb   Control Circuit 11 in·lb   Document Number)   CB_SE_70920A1M2   CCC_2011010303465426   UL_20091127-E252354-2-1   1SBD250166C2000   DNV_E11683   EAC_RU C-FR ME77 B01006   GL_3786612HH   GOST_POCCFR.ME77.B06804.pdf
Technical UL/CSA Tightening Torque UL/CSA: Certificates and Declarations (Do CB Certificate: CCC Certificate: cUL Certificate: Declaration of Conformity - CE: DNV Certificate:	after 2008 Q1   Auxiliary Circuit 11 in·lb   Control Circuit 11 in·lb   Document Number)   CB_SE_70920A1M2   CCC_2011010303465426   UL_20091127-E252354-2-1   1SBD250166C2000   DNV_E11683   EAC_RU C-FR ME77 B01006   GL_3786612HH   GOST_POCCFR.ME77.B06804.pdf   LRS_C1400038
Technical UL/CSA Tightening Torque UL/CSA: Certificates and Declarations (Do CB Certificate: CCC Certificate: cUL Certificate: Declaration of Conformity - CE: DNV Certificate: EAC Certificate: GL Certificate: GL Certificate: GST Certificate: LR Certificate: RINA Certificate:	after 2008 Q1   Auxiliary Circuit 11 in·lb   Control Circuit 11 in·lb   Doument Number)   CB_SE_70920A1M2   CCC_2011010303465426   UL_20091127-E252354-2-1   1SBD250166C2000   DNV_E11683   EAC_RU C-FR ME77 B01006   GL_3786612HH   GOST_POCCFR.ME77.B06804.pdf   LRS_C1400038   RINA_ELE084013XG
Technical UL/CSA Tightening Torque UL/CSA: Certificates and Declarations (Do CB Certificate: CCC Certificate: cUL Certificate: Declaration of Conformity - CE: DNV Certificate: EAC Certificate: EAC Certificate: GST Certificate: LR Certificate: RINA Certificate: RINA Certificate: RMRS Certificate:	after 2008 Q1   Auxiliary Circuit 11 in·lb   Control Circuit 11 in·lb   Doument Number)   CB_SE_70920A1M2   CCC_2011010303465426   UL_20091127-E252354-2-1   1SBD250166C2000   DNV_E11683   EAC_RU C-FR ME77 B01006   GL_3786612HH   GOST_POCCFR.ME77.B06804.pdf   LRS_C1400038   RINA_ELE084013XG   RMRS_1300132124
Technical UL/CSA Tightening Torque UL/CSA: Certificates and Declarations (Do CB Certificate: CCC Certificate: cUL Certificate: Declaration of Conformity - CE: DNV Certificate: EAC Certificate: EAC Certificate: GL Certificate: GOST Certificate: LR Certificate: RINA Certificate: RINA Certificate: RMRS Certificate: ROHS Information:	after 2008 Q1   Auxiliary Circuit 11 in·lb   Control Circuit 11 in·lb   Doument Number)   CB_SE_70920A1M2   CCC_2011010303465426   UL_20091127-E252354-2-1   1SBD250166C2000   DNV_E11683   EAC_RU C-FR ME77 B01006   GL_3786612HH   GOST_POCCFR.ME77.B06804.pdf   LRS_C1400038   RINA_ELE084013XG   RMRS_1300132124

Provider information/Impressum© Copyright 2015 ABB. | Cookies and privacy policy | Login

👔 Facebook | 🗾 Twitter